

FAB10URDSN3

Product family Installation Category Defrost

Hinge position EAN code Refrigerator Free-standing Single door Automatic for refrigerator, manual for freezer Left 8017709326159



Aesthetic

| Aesthetics |
|-------------------------------|
| Color |
| Finishing |
| Decoration / Special color |
| Collaborations |
| Handle |

Retro-style White Glossy Snoopy Smeg & Peanuts External Handle color Logo color Side material Side color Logo Chromed Chromed Steel White Applied

Refrigerator compartment features

| No. of adjustable | 2 | Crisper cover | Yes |
|-------------------------------|----------|-----------------------|-------|
| shelves | | Type of crisper cover | Glass |
| Number of fruit and | 1 | Refrigerator lighting | Yes |
| vegetables drawers | | Refrigerator lighting | LED |
| Type of adjustable shelves | Glass | | |
| Crisper drawer type | Standard | | |

Refrigerator Inner Door

| Number of adjustable | 2 | No. of bottle shelves | 1 |
|----------------------|---|-----------------------|---|
| door shelves | | | |

Freezer features



Internal freezer compartment Yes

Other technical features

| Temperature setting type |
|--------------------------|
| No. of compressors |
| Refrigerant gas type |
| Compressor type |
| Foam agent |

Electro-mechanical 1 R600a Standard Cyclopentane

Performance / Energy Label NEW

| Total volume | 4.48 cu. ft. | Refrigerator volume | 3.85 cu. ft. |
|------------------|------------------|---------------------|--------------|
| Noise level | 37 dB(A) re 1 pW | Climatic class | SN, N, ST, T |
| Freezer capacity | 0.64 cu. ft. | | |

Electrical Connection

| Plug | (A) USA & Mexico | Voltage (V) | 120 V |
|-----------------------|------------------|-------------------|----------|
| Electrical connection | 110 W | Frequency (Hz) | 60 Hz |
| rating | | Power cord length | 70 7/8 " |
| Current | 1,25 A | | |

297

120°

1049





533

1

516





Symbols glossary (TT)

*

The automatic defrost system works by automatically defrosting at regular intervals eliminating the need to defrost altogether.



LED interior lighting: is a more energy efficient and long lasting way of illuminating the interior of the appliance.